

10 15

5

10

15

20

25
17W

45
LAW OFFICES
DAVID NEWMAN
& ASSOCIATES, P.C.
CENTENNIAL SQUARE
P.O. BOX 2728
LA PLATA, MD 20646
(301) 934-6100

30

programming said programmable-matched filter, responsive to the data-control signal, to have the programmable-impulse response matched to the data-chip-sequence signal; and despread-
despreading, with the programmable-matched filter matched to the data-chip-sequence signal, the data-spread-spectrum channel as a despread-data-bit-sequence signal.

2. The method as set forth in claim 1, with the step of despreading the pilot-spread-spectrum channel further including the steps of:

despreading, from the received spread-spectrum signal, an in-phase component of the pilot-spread-spectrum channel as a despread-in-phase component of the despread-pilot-bit-sequence signal; and

despreading, from the received spread-spectrum signal, a quadrature-phase component of the pilot-spread-spectrum channel as a despread-quadrature-phase component of the despread-pilot-bit-sequence signal.

3. The method as set forth in claim 1 or 2 with the step of despreading the data-spread-spectrum channel further including the steps of:

despreading, from the received spread-spectrum signal, an in-phase component of the data-spread-spectrum channel as a despread-in-phase component of the despread-data-bit-sequence signal; and

5

despreading, from the received spread-spectrum signal,
a quadrature-phase component of the data-spread-spectrum channel
as a despread-quadrature-phase component of the despread-data-
bit-sequence signal.

4. The method as set forth in claim 2 with the step of
filtering the despread pilot-bit-sequence signal further
including the steps of:

generating an in-phase-peak-pilot-correlation signal
in response to the despread-in-phase component of the despread-
pilot-bit-sequence signal matching an in-phase-frame-impulse
response; and

generating a quadrature-phase peak-pilot-correlation
signal in response to the despread-quadrature-phase component of
the despread-pilot-bit sequence signal matching a quadrature-
phase-frame-impulse response.

~~6~~ 6. The method as set forth in claim 1, further including
the step of demodulating the despread-data-bit-sequence signal
as a received data-bit-sequence signal.

~~5~~ 5. The method as set forth in claim 2 further including
the step of demodulating an in-phase component of the despread-
data-bit-sequence signal and a quadrature-phase component of the
despread-data-bit-sequence signal, as a received-data-bit-
sequence signal.

08821003-032097

Sub A → 7. A method, using a programmable-matched filter having a first plurality of taps and a frame-matched filter having a second plurality of taps with a spread-spectrum receiver on a received spread-spectrum signal to generate a code having a first plurality of chips, the first plurality of chips being equal to a product of the first plurality of taps and the second plurality of taps, the received spread-spectrum signal having a pilot-spread-spectrum channel generated from spread-spectrum processing a pilot-bit-sequence signal with a pilot-chip-sequence signal and a data spread-spectrum channel generated from spread-spectrum processing a data-bit-sequence signal with a data-chip-sequence signal, comprising the steps of:

generating a replica of the pilot-chip-sequence signal;

generating a replica of the data-chip-sequence signal;
generating, responsive to a peak-pilot correlation signal, a pilot-control signal;

programming said programmable-matched filter to set the first plurality of taps of said programmable-matched filter to have a programmable-impulse response matched to the pilot-chip-sequence signal;

despreading the pilot-spread-spectrum channel as a despread-pilot-bit-sequence signal, each bit of the despread-pilot-bit-sequence having a second plurality of chips, a number of the second plurality of chips being equal to a number of the first plurality of taps;

outputting, on the basis of one output for every second plurality of chips, the despread-pilot-bit-sequence signal to the frame-matched filter;

filtering, with said frame-matched filter having a frame-impulse response matched to the pilot-bit-sequence signal, the despread-pilot-bit-sequence signal, each of the second plurality of taps of said frame-matched filter for correlating with a respective bit of the despread-pilot-bit-sequence signal;

generating a peak-pilot-correlation signal in response to a frame of the despread-pilot-bit-sequence signal matching the frame-impulse response of the frame-matched filter;

programming said programmable-matched filter, responsive to the peak-pilot-correlation signal, to have the programmable-impulse response matched to the data-chip-sequence signal; and

despreading the data-spread-spectrum channel as a despread-data-bit-sequence signal.

8. The method as set forth in claim 7, with the step of despreading the pilot-spread-spectrum channel further including the steps of:

despreading an in-phase component of the pilot-spread-spectrum channel as a despread-in-phase component of the despread-pilot-bit-sequence signal; and

despreading a quadrature-phase component of the pilot-spread-spectrum channel as a despread-quadrature-phase component of the despread-pilot-bit-sequence signal.

9. The method as set forth in claim 7 or 8 with the step of despreading the data-spread-spectrum channel further including the steps of:

despreading an in-phase component of the data-spread-spectrum channel as a despread-in-phase component of the despread-data-bit-sequence signal; and

despreading a quadrature-phase component of the data-spread-spectrum channel as a despread-quadrature-phase component of the despread-data-bit-sequence signal.

10. The method as set forth in claim 8 with the step of generating a peak-pilot-correlation signal further including the steps of:

generating an in-phase-peak-pilot-correlation signal in response to the despread-in-phase component of the despread-pilot-bit-sequence signal matching an in-phase-frame-impulse response; and

generating a quadrature-phase peak-pilot-correlation signal in response to the despread-quadrature-phase component of the despread-pilot-bit sequence signal matching a quadrature-phase-frame-impulse response.

¹²
~~11~~. The method as set forth in claim 7, further including the step of demodulating the despread-data-bit-sequence signal as a received data-bit-sequence signal.

¹¹
~~12.~~ The method as set forth in claim 8 further including the step of demodulating an in-phase component of the despread-data-bit-sequence signal and a quadrature-phase component of the despread-data-bit-sequence signal, as a received-data-bit-sequence signal.

5

08821003-032097